

POWER SPECIFICATIONS

PROTEUS XR/a 50kW or 65kW REV. DATE: 21.JUN.14

VOLTAGE PRIMARY SOURCE IS REQUIRED FOR ALL INSTALLATIONS.
 RANGE OF LINE VOLTAGES :
 NOMINAL LINE VOLTAGE OF 380 TO 480, 3 PHASE, WITHOUT NEUTRAL,
 50 OR 60 Hz.

REQUIRED POWER SUPPLY: WYE DISTRIBUTION

MAXIMUM DAILY VOLTAGE VARIATION MUST FALL WITHIN ONE OF THE RANGES IN TABLE A.

**TABLE A
 ALLOWABLE
 INPUT
 VOLTAGES/
 CURRENT
 DEMAND**

NOMINAL VOLTAGE	NORMAL RANGE ±10 PERCENT	CURRENT (AMPS)		MINIMUM STANDARD OVERCURRENT PROTECTION
		MAX. MOMENTARY	CONTINUOUS	
380	342-418	148	7	80-A
400	360-440	140	6.6	70-A
415	373-456	135	6.4	70-A
440	396-484	127	6	70-A
460	414-506	122	5.8	70-A
480	432-528	117	5.5	60-A

ALL CALCULATIONS BASED UPON NOMINAL VOLTAGE

NOTE LOW LINE CONDITIONS MAY INHIBIT SOME HIGH kVp TECHNIQUES. THE GENERATOR AUTOMATICALLY ESTABLISHES THESE INHIBITS BASED ON ACTUAL LINE CONDITIONS AND SYSTEM REGULATION.

PHASE-BALANCE. PHASE-TO-PHASE VOLTAGES MUST BE WITHIN +2 PERCENT OF THE LOWEST PHASE-TO-PHASE VOLTAGE. MAXIMUM ALLOWABLE TRANSIENT VOLTAGE EXCURSIONS ARE 2.5 PERCENT OF RATED LINE VOLTAGE AT A MAXIMUM DURATION OF 5 CYCLES AND FREQUENCY OF 10 TIMES PER HOUR.

POWER DEMAND CONTINUOUS POWER DEMAND =4.6 KVA. (MAX DEMAND = 97 KVA)

**TABLE B
 MAXIMUM
 MOMENTARY
 POWER
 DEMAND.**

DEMAND	PROTEUS/DEFINIUM
kVa * POWER FACTOR AT	97 0.73
mA	630
kVp	80

* DEMAND INCLUDES POWER FOR ENTIRE SYSTEM. LINE VOLTAGE REGULATION AT MAXIMUM POWER DEMAND MUST BE LESS THAN OR EQUAL TO 6 PERCENT.

DISTRIBU-TION TRANS-FORMER FOR A SINGLE UNIT INSTALLATION, THE MINIMUM TRANSFORMER SIZE IS 112.5 KVA. SYNTHESIZED POWER FEED IS NOT ACCEPTABLE



FEEDER TABLE

PROTEUS XR/a 50kW or 65kW WITH 80 AMP BREAKER

REV. DATE: 15.Apr.11

- CALCULATIONS BASED UPON NOMINAL VOLTAGE, WIRE SIZE IN AWG.
- RECOMMENDED FEEDER SIZES FROM DISTRIBUTION TRANSFORMER TO THE POWER CABINET
- NEUTRAL MUST BE TERMINATED INSIDE THE MAIN DISCONNECT PANEL AND NOT AT ANY GE CABINET.
- THE GROUNDING CONDUCTOR WILL BE THE SAME SIZE AS THE FEEDER WIRES. THIS GROUND WILL RUN FROM THE EQUIPMENT BACK TO THE FACILITY POWER SOURCE/MAIN GROUNDING POINT AND ALWAYS TRAVEL IN THE SAME CONDUIT WITH THE FEEDERS AND NEUTRAL.
- * MINIMUM WIRE SIZE FOR CIRCUIT BREAKER, BASED ON RECOMMENDED OVERCURRENT PROTECTION.
- FOR A FULL SYSTEM UPS, REFER TO ELECTRICAL DETAILS FOR UPS FEEDER WIRES.

NOTE: POWER RUN FROM WALL BOX/DUCT TO GENERATOR MUST BE WELDING CABLE OR EQUIVALENT.

RUN LENGTH IN FEET	POWER SUPPLY VOLTAGE					
	342-418 380	360-440 400	373-456 420	396-484 440	414-506 460	432-528 480
SIZE OF FEEDERS AND GROUND WIRES (AWG)						
50	* 4	* 4	* 4	* 4	* 4	* 4
100	3	* 4	* 4	* 4	* 4	* 4
150	2	2	2	3	3	* 4
200	1/0	1	1	2	2	2
250	2/0	2/0	1/0	1/0	1	1
300	3/0	2/0	2/0	1/0	1/0	1/0
350	4/0	3/0	3/0	2/0	2/0	1/0
400	250M	4/0	4/0	3/0	3/0	2/0
450	300M	250M	4/0	4/0	3/0	3/0